

POWER DIVIDERS, RESISTIVE

SMA, up to 18 GHz, 1 Watt

SPECIFICATIONS:

Models: 6014F-01, 6014F-02, 6014F-03

RoHS
Compliant

AEROFLEX
A passion for performance.

Electrical:

Frequency Range _____ See Below
 Standard Freq. Values _____ 6, 12.4 and 18 GHz
 Input VSWR _____ See Below
 Impedance _____ 50 Ohms
 Insertion Loss _____ See Below
 Phase Tracking _____ See Below
 Input Power _____ 1 Watt Avg. @ 25°C
 _____ Derated Linearly to 0.Watts @ +125°C
 Operating Temp Range _____ -65°C to +125°C

Mechanical:

SMA Connectors _____ Passivated Stainless Steel
Mates IAW MIL-STD-348
 Housing _____ Passivated Stainless Steel
 Conductors _____ Gold Plated Beryllium Copper

Model Number: 6014F-01


Frequency Range _____ DC - 12.4 GHz
 Input VSWR _____ 1.20:1 Max.
 Insertion Loss _____ 6dB Nominal
 Phase Tracking _____ $\pm 2^\circ$
 (between output ports)
 Amplitude Tracking _____ 0.4dB

Model Number: 6014F-02

Frequency Range _____ DC - 18 GHz
 Input VSWR _____ 1.30:1 Max.
 Insertion Loss _____ 7.5dB Nominal
 Phase Tracking _____ $\pm 3^\circ$
 (between output ports)
 Amplitude Tracking _____ 0.5dB

Model Number: 6014F-03

Frequency Range _____ DC - 6 GHz
 Input VSWR _____ 1.20:1 Max.
 Insertion Loss _____ 6dB Nominal
 Phase Tracking _____ $\pm 2^\circ$
 (between output ports)
 Amplitude Tracking _____ 0.4dB



Note: Dimensions in Brackets are Expressed in Millimeters and are for Reference Only.
 Design specifications are subject to change without notice.
 Contact factory for technical specifications before purchasing or use.

6014F: REV E

AEROFLEX
INMET

Aeroflex / Inmet, Inc. • 300 Dino Drive, Ann Arbor, MI 48103 • U.S.A.
 888-244-6638 or 734-426-5553 • FAX: 734-426-5557
 www.aeroflex.com/inmet • inmet-sales@eroflex.com